Mini installation beacon / MC55 MC55 RGY Cable 24VDC



ļ


| Part No.: | 240.210.55 | |
|------------------------------|------------|--------------------------------|
| Series: | MC55 | CC CA |
| MECHANI | CAL DATA | |
| Height | | 71 mm |
| Diameter | | 55 mm |
| Materials | | PC |
| | | PC/ABS |
| Dome colour | | Tranclucent |
| Housing colour | | Black |
| Protection category | | IP65 |
| Connection | | Cable |
| Cable length | | 1450 mm |
| Tension relief | | Pull-out protection |
| Type of fixing | | Built-in mounting |
| Working temperature minimum | | -20°C |
| Working temperature maximum | | +50°C |
| Weight with packaging | | 125 g |
| Product weight | | 104 g |
| ELECTRIC | AL DATA | |
| Operating voltage | | 24V |
| Operating voltage type | | DC |
| Operating voltage tolerance | | +/- 10% |
| Rated operational voltage | | 24 VDC |
| Rated operational current | | 45 mA |
| Rated inrush current | | <150mA |
| Protection class | | Protection class 2 |
| Pollution degree | | 3 In the connection area: 2 |
| OPTICAL | DATA | |
| Light source | | LED |
| Light colour | | MC 3 colours |
| Optical signal image | | Permanent |
| Service life optical | | 50,000 h maximum |
| APPROVA | | |
| Conforms with CE | | Yes |
| Conforms with RoHS directive | | Yes |
| WEEE | | Yes |
| Conforms with ATEX-directive | | No |
| Conforms with CCC | | No |
| Conforms with UL | | No |

For additional installation and mounting information, refer to the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.

Mini installation beacon / MC55 MC55 RGY Cable 24VDC

| Conforms with FCC | No |
|-------------------------------|-----------------------|
| Conforms with IC | No |
| EAC certificate available | Yes |
| Conforms with UKCA (Importer) | Yes (WERMA (UK) Ltd.) |
| Conforms with AS-I | No |
| ICAO Certification | No |
| Conforms with DNV | No |
| Conforms with RoHS CN | 25 years |
| Conforms with VdS | No |
| MTTF-value [years] | 207 |

DRAWING



Provide the appropriate user guide at www.werma.com. This printed copy is for information only and is subject to alteration.